

Power max

Trade Series
GENERATOR

5500W

ELECTRIC START PORTABLE GENERATOR

XPR5500ES

SKU# 327898



**DIGITAL
AVR**

**25L
FUEL
TANK**

**UP TO
8 hrs
USE ON
FULL TANK**

**2x
230V
AC POWER
OUTLETS**

**3 in 1
DISPLAY**

**VOLTS, HERTZ
& HOURS**

**USB
Function**

5500W PEAK POWER.

**IDEAL FOR CAMPING
AND HOME USE APPLICATIONS.**

DIGITAL AVR - ensures a precise microprocessor controlled output

DUAL USB CHARGING PORTS - for charging of digital devices, phones etc.

AC OUTPUT - great for 230V applications - operating lighting, small fridge/freezers, heaters and much more.

DIGITAL HOUR METER - with voltage, hertz and total hours displayed.

DURABLE STEEL ROLL CAGE FRAME AND ANTI-VIBRATION ENGINE MOUNTS

LARGE CAPACITY MUFFLER FOR QUIET OPERATION - minimizes engine noise, ideal for use anywhere a quiet source of power is required.

LARGE 25 LITRE FUEL TANK - ensures up to 8 hours of continuous operation at full load.

HIGH PERFORMANCE AIR CLEANER SYSTEM - greatly reduces engine wear and improves performance.

SIMPLE AND RELIABLE ELECTRONIC IGNITION SYSTEM - makes starting easier every time.

THERMAL OVERLOAD CIRCUIT BREAKERS - cuts the power in the event of an electrical overload offering greater safety.

HEAVY DUTY NO FLAT WHEELS.

AC Output:	230V AC ~ 50Hz
Rated Power:	5000W
Peak Power:	5500W
Phase:	Single
Noise Level:	78dBA
Power Factor:	COS ϕ = 1
Displacement:	389cc
Engine:	OHV 4 Stroke
Speed:	3000RPM
Fuel Tank :	25L
Fuel:	Unleaded
Net Weight:	95kg

IMPORTANT NOTICE:

The POWERMAX Generator Series are NOT guaranteed to run sensitive electronic equipment like computers, TVs or other electronic appliances. While the digital AVR regulation system will compensate for most power fluctuations, there is still the possibility of momentary voltage fluctuations due to engine RPM that may harm sensitive electronics. For powering sensitive electronics an Inverter Generator is recommended. Ask your POWERMAX Distributor for details.



www.powermax.co.nz