

Power max

GENERATOR

2200W

2.8kVA PORTABLE GENERATOR

XPR2500

SKU# 327895

15L
FUEL
TANK

UP TO
10 hrs
AT 50%
LOAD

2x
230V
AC POWER
OUTLETS



3 in 1
DISPLAY

VOLTS, HERTZ
& HOURS

AC Output: 230V AC ~ 50Hz

Rated Power: 2000W

Peak Power: 2200W

kVA 2.8

Phase: Single

Noise Level: 76dBA

Engine: OHV 4 Stroke

Fuel Tank : 15L

Fuel: Unleaded

Net Weight: 43kg

IMPORTANT NOTICE:

The POWERMAX Generator Series are NOT guaranteed to run sensitive electronic equipment like computers, TVs or other electronic appliances. While the AVR regulation system will compensate for most power fluctuations, there is still the possibility of momentary voltage fluctuations due to engine RPM that may harm sensitive electronics. For powering sensitive electronics an Inverter Generator is recommended. Ask your POWERMAX Distributor for details.

2200W PEAK POWER.

IDEAL FOR CAMPING AND HOME USE APPLICATIONS.

AC OUTPUT - great for 230V applications - operating lighting, small fridge/freezers, fans and much more.

DURABLE STEEL ROLL CAGE FRAME AND ANTI-VIBRATION ENGINE MOUNTS

LARGE CAPACITY MUFFLER FOR QUIET OPERATION- minimizes engine noise, ideal for use anywhere a quiet source of power is required.

LARGE 15 LITRE FUEL TANK - ensures up to 10 hours of continuous operation at 50% load.

HIGH PERFORMANCE AIR CLEANER SYSTEM - greatly reduces engine wear and improves performance.

SIMPLE AND RELIABLE ELECTRONIC IGNITION SYSTEM- makes starting easier every time.

THERMAL OVERLOAD CIRCUIT BREAKERS- cuts the power in the event of an electrical overload offering greater safety.



www.powermax.co.nz